

Impedance meter for loudspeakers or low impedance loudspeaker lines, with 100 or 70 V line transformer.
An essential PA installation tool.
Allows the loudspeaker line to be checked and measures the resulting impedance.



MI-21

CHARACTERISTICS	Impedance meter at 1 kHz for loudspeaker lines.
	Allows the impedance of loudspeaker lines to be checked and the necessary power in a 100 or 70 V line installation to be estimated, in order to choose the correct amplifier.
	3 measurement scales: 200 Ohm, 2 kOhm and 20 kOhm.
	Easy to read LCD screen.
INPUTS	Power meter for 70 and 100 V line loudspeakers.
	Easy to use.
RESOLUTION (MEASUREMENT A	2 banana plugs to connect the test leads.
	200 Ohm: 0.1 Ohm ($\pm 1\% \pm 2$)
	2 kOhm: 1 Ohm ($\pm 1\% \pm 2$)
POWER SUPPLY	20 kOhm: 10 Ohm ($\pm 1\% \pm 2$)
	9 V DC, 1 x 9V 6LR61 type battery
DIMENSIONS	86 x 182 x 38 mm depth
WEIGHT	0.4 kg
ACCESSORIES	Rubber protector
	2 sets of test leads: with alligator clip terminals and precision tips